

# Frequency Standards

FS740 — GPS Time and Frequency System

**GMP**  
GENERAL  
MICROTECHNOLOGY  
& PHOTONICS



## FS740 GPS Time and Frequency System

- **GPS disciplined 10 MHz reference**
- **$1 \times 10^{-13}$  long term stability**
- **Time tag events to UTC or GPS**
- **Sine, square, triangle, IRIG-B output**
- **Frequency counter with 12 digits/s**
- **Built-in distribution amplifiers**
- **Ethernet & RS-232 interfaces**

The FS740 provides a 10 MHz frequency reference which is disciplined by GPS with a long term stability of better than  $1 \times 10^{-13}$ . The instrument can also time tag external events with respect to UTC or GPS and measure the frequency of user inputs. The instrument has DDS synthesized frequency outputs, adjustable rate (and width) pulse outputs, and an AUX output for arbitrary waveforms including an IRIG-B timecode output.

### Standard, OCXO, or Rubidium Timebase

The standard timebase provides  $1 \times 10^{-9}$  short term frequency stability and phase noise of less than  $-100$  dBc/Hz at 10 Hz offset. An optional OCXO (ovenized crystal oscillator) timebase provides  $1 \times 10^{-11}$  short term frequency stability and phase noise of less than  $-130$  dBc/Hz at 10 Hz offset. An optional rubidium timebase provides  $1 \times 10^{-12}$  short term frequency stability, phase noise of less than  $-130$  dBc/Hz at 10 Hz offset, and a long term holdover (lost GPS signal) of better than  $1 \mu\text{s/day}$ .

Both optional timebases (OCXO or rubidium) provide a dramatic improvement in the holdover characteristics, a 30 dB reduction in the phase noise and a tenfold reduction in the TDEV. There are some users who would not need this performance improvement. For example, users who only need time tags with  $1 \mu\text{s}$  accuracy or frequency measurements with 1:108 accuracy could use the standard timebase.

**GPS Receiver**

The FS740 provides bias for a remote active GPS antenna. The unit's GPS receiver tracks up to 12 satellites, will automatically survey and fix its position, then use all received signals to optimize its timing solution. The FS740 time-tags the 1 pps output from the receiver, corrects the result for the receiver's sawtooth error, then phase locks the timebase to the GPS 1 pps with an adjustable time constant between 1 minute and 10 hours. The TDEV (rms timing deviation) between two instruments is a few nanoseconds.

If the GPS signal is lost, the timebase is left at the last locked frequency value. The timebase will age or drift in frequency by up to  $\pm 2$  ppm (for the standard timebase),  $\pm 0.05$  ppm per year and  $\pm 0.002$  ppm (0 to 45°C) for the OCXO, and  $\pm 0.001$  ppm per year and  $\pm 0.0001$  ppm (0 to 45°C) for the rubidium timebase.

**GNSS Antennas**

You may choose to purchase a GPS antenna from SRS, or a third party, or use an existing GPS antenna at their facility. SRS timing receivers require a net gain (after cable losses) of +20 dBi to +32 dBi, which is a very common level from a variety of available active antennas and typical cable lengths. The antenna input to SRS timing receivers have a female BNC connector, provide +5 V bias, and have a 50  $\Omega$  input impedance.

SRS offers two antenna solutions, both of which have LNAs. All systems components have a 50  $\Omega$  characteristic impedance. For antenna details click [here](#).

**Graphical User Interface**

A GUI (graphical user interface) allows the user to configure the instrument and see the results of time and frequency measurements. The instrument can be configured in one of three modes: There are two user inputs (one on the front, one on the rear panel) for frequency and time tag events. The inputs have adjustable thresholds and slopes. Frequencies are measured with a precision of  $1 \times 10^{-11}$  in 1 s,  $1 \times 10^{-12}$  in 10 s, and  $1 \times 10^{-13}$  in 100 s. Time tags are reported with 1 ps resolution which is comparable to the short term stability of

the OCXO and rubidium timebases. Time tags will have an error of about 10 ns rms with respect to UTC or GPS time.

**Front and Rear Panel**

The FS740 has a rear-panel low phase noise ( $-130$  dBc/Hz at 10 Hz offset) 10 MHz sine output with an amplitude of 1 Vrms. Up to 15 additional copies of the 10MHz output are available via optional rear panel outputs.

The FS740 has front-panel and rear-panel SINE outputs which provide sine outputs from 1  $\mu$ Hz to 30.1 MHz with 1  $\mu$ Hz resolution, or a fixed 100 MHz, with adjustable amplitude from 100 mV to 1.2 V rms. Up to 15 additional copies of the SINE outputs are available via optional rear panel outputs.

The FS740 has front-panel and rear-panel PULSE outputs which can provide low jitter ( $< 5$  ps,rms) pulses from 1  $\mu$ Hz to 30.1 MHz. The PULSE outputs have adjustable phase with respect to UTC and the pulse width can be set as narrow as 5 ns, or as wide as the entire pulse period minus 5 ns, with 10 ps resolution. Up to 15 additional copies of the PULSE outputs are available via optional rear panel outputs.

The FS740 has front-panel and rear-panel AUX output which can generate standard or arbitrary waveforms (sine, ramp, triangle, etc.) The AUX output can also provide an IRIG-B timecode output. Both width coded pulses and amplitude modulated sine waves (with carrier frequencies from 100 Hz to 1 MHz) are available for the IRIG-B outputs. Up to 15 additional copies of the AUX output are available via optional rear panel outputs.

A rear-panel alarm relay is set if power is lost or under user defined conditions including: timebase fault, loss of GPS reception, or any failure to maintain phase lock between the timebase and GPS. The relay has both normally open and closed outputs.

**Distribution Amplifiers**

Optional distribution amplifiers, each providing six additional rear-panel outputs for the 10 MHz, SINE, PULSE, AUX or IRIG-B outputs, can be installed. Up to three distribution amplifiers can be installed and configured from the front panel. Each output has its own driver which provides high isolation between outputs.



*FS740 rear panel*

## FS740 Specifications

### Standard TCXO Timebase

Oscillator type	Oven controlled, 3rd OT, AT-cut crystal
Stability	$<2 \times 10^{-6}$ (20 to 30 °C)
Aging	$<5$ ppm/year (undisciplined to GPS)

### OCXO Timebase

Oscillator type	Oven controlled, 3rd OT, AT-cut crystal
Stability	$<1 \times 10^{-6}$ (20 to 30 °C)
Aging	$<0.2$ ppm/year (undisciplined to GPS)

### Rubidium Timebase

Oscillator type	Oven controlled, 3rd OT, AT-cut crystal
Physics package	Rb vapor frequency discriminator
Stability	$<1 \times 10^{-10}$ (20 to 30 °C)
Aging	$<0.0005$ ppm/year (undisciplined to GPS)

### GPS Receiver

Satellite acq. time	Less than 1 minute (typ.)
Almanac acq. time	Approximately 15 minutes when continuously tracking satellites
Optimized for static applications	Over determined clock mode enables receiver to use all satellites for timing Gates
Accuracy of UTC	$<100$ ns
Time wander	$<15$ ns rms (in over determined clock mode)
Antenna delay correction range	$\pm 0.1$ s

### Sine Output (50 $\Omega$ load)

Frequency range	1 mHz to 30.1 MHz
Frequency resolution	1 $\mu$ Hz
Frequency error	$<10$ pHz + timebase error $\times$ FC
Phase settability	1 mDeg
Phase accuracy	$<1$ ns (to internal reference)
Amplitude	10 mVpp to 1.414 Vpp
Amplitude resolution	$<1$ %
Amplitude accuracy	$\pm 5$ %
Harmonics	$<-40$ dBc
Spurious	$<-70$ dBc
Output coupling	DC, 50 $\Omega \pm 2$ %
User load	50 $\Omega$
Reverse protection	$\pm 5$ VDC

### Aux Output (50 $\Omega$ load)

Output options	Sine, Triangle, Square, 100 MHz, AM IRIG-B
Frequency range	1 mHz to 10 MHz (sine)

Frequency resolution	1 mHz to 1 MHz (triangle or square)
Frequency error	100 MHz (100 MHz sine)
Phase settability	1 kHz (AM IRIG-B)
Amplitude	1 $\mu$ Hz $<10$ pHz + timebase error $\times$ FC 1 mDeg (cannot adjust phase of 100 MHz sine output)
Amplitude resolution	10 mVpp to 1.414 Vpp (sine, triangle, square)
Amplitude accuracy	2.75 dBm $\pm 0.5$ dBm (100 MHz)
Harmonics	$<1$ %
Spurious	$\pm 5$ %
Output coupling	$<-40$ dBc
User load	$<-70$ dBc
Reverse protection	DC, 50 $\Omega \pm 2$ %
	50 $\Omega$
	$\pm 5$ VDC

### Pulse Output

Output options	Period/width, Freq/duty, Pulse IRIG-B
Period	40 ns to 1000 s
Width	5 ns to (Period - 5 ns)
Period/width resolution	1 ps
Frequency range	1 mHz to 25 MHz
Frequency resolution	1 $\mu$ Hz
Frequency error	$<10$ pHz + timebase error $\times$ FC
Jitter	$<50$ ps rms
Level	+5 V CMOS logic
Transition time	$<2$ ns
Source impedance	50 $\Omega$

### Time and Frequency Input

Time tag resolution	1 ps
Time tag jitter (rms)	$<50$ ps
Frequency resolution	1 $\mu$ Hz
Measurement stability	$<5 \times 10^{-12}$ (1 s gate), synchronous with fast averaging enabled $<5 \times 10^{-11}$ otherwise

### Computer Interfaces

Ethernet (LAN)	10/100 Base-T, TCP/IP & DHCP
RS-232	4.8k-115.2k baud, RTS/CTS flow

### General

AC power	90 to 264 VAC, 90 W 47 to 63 Hz with PFC
EMI Compliance	FCC Part 15 (Class B), CISPR-22 (Class B)
Dimensions	8.5" $\times$ 3.5" $\times$ 13" (WHL)
Weight	10 lbs.
Warranty	One year parts and labor on defects in materials and workmanship